

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.

PR1... relay base, for miniature power relays or miniature switching relays with 1 or 2 changeover contacts or solid-state relays with the same design, 1/3-level version, spring-cage connections, plug-in option for input/interference suppression modules



Your advantages

- Relay base family for assembly with 1- or 2-changeover contact relay or solid-state relays
- Relay retaining bracket with labeling field and ejection function
- Plug-in input/interference suppression modules

Commercial data

Item number	2833534
Packing unit	1 pc
Note	Made to order (non-returnable)
Sales key	C463
Product key	CK6322
Catalog page	Page 373 (C-7-2013)
GTIN	4017918933784
Weight per piece (including packing)	55 g
Weight per piece (excluding packing)	45.84 g
Customs tariff number	85366990
Country of origin	CN

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



Technical data

Product properties

Product type	Relay socket
--------------	--------------

Electrical properties

Nominal voltage U_N	300 V AC/DC
Nominal current I_N	10 A

Connection data

Input side

Connection method	Spring-cage connection
Stripping length	10 mm
Conductor cross section rigid	0.5 mm ² ... 1.5 mm ²
Conductor cross section flexible	0.5 mm ² ... 1.5 mm ²
Conductor cross section AWG	26 ... 16

Output side

Connection method	Spring-cage connection
Stripping length	10 mm
Conductor cross section rigid	0.5 mm ² ... 1.5 mm ²
Conductor cross section flexible	0.5 mm ² ... 1.5 mm ²
Conductor cross section AWG	26 ... 16

Dimensions

Width	16 mm
Height	97 mm
Depth Retaining bracket	72 mm (EL1-P16)
	80 mm (EL1-P25)

Environmental and real-life conditions

Ambient conditions

Ambient temperature (operation)	-25 °C ... 85 °C
---------------------------------	------------------

Mounting

Mounting type	DIN rail mounting
Mounting position	any

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

Classifications

ECLASS

ECLASS-11.0	27371603
-------------	----------

UNSPSC

UNSPSC 21.0	39122335
-------------	----------

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

Environmental product compliance

China RoHS	
Environment friendly use period (EFUP)	<div>EFUP-50</div> <div>An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.</div>
EU REACH SVHC	
REACH candidate substance (CAS No.)	No substance above 0.1 wt%

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

Mandatory accessories

REL-MR- 12DC/21HC - Single relay

2961309

<https://www.phoenixcontact.com/us/products/2961309>




Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 12 V DC

REL-MR- 24DC/21HC - Single relay

2961312

<https://www.phoenixcontact.com/us/products/2961312>



Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 48DC/21HC - Single relay

2834821

<https://www.phoenixcontact.com/us/products/2834821>




Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 48 V DC

REL-MR- 60DC/21HC - Single relay

2961325

<https://www.phoenixcontact.com/us/products/2961325>



Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, 60 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-110DC/21HC - Single relay

2961338

<https://www.phoenixcontact.com/us/products/2961338>




Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 110 V DC

REL-MR- 24AC/21HC - Single relay

2961406

<https://www.phoenixcontact.com/us/products/2961406>



Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 24 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-120AC/21HC - Single relay

2961419

<https://www.phoenixcontact.com/us/products/2961419>




Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 120 V AC

REL-MR-230AC/21HC - Single relay

2961422

<https://www.phoenixcontact.com/us/products/2961422>



Plug-in miniature power relay, with power contact for high continuous currents, 1 changeover contact, input voltage 230 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 12DC/21HC AU - Single relay

2961532

<https://www.phoenixcontact.com/us/products/2961532>




Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 12 V DC

REL-MR- 24DC/21HC AU - Single relay

2961545

<https://www.phoenixcontact.com/us/products/2961545>



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-110DC/21HC AU - Single relay

2961561

<https://www.phoenixcontact.com/us/products/2961561>




Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 110 V DC

REL-MR- 24AC/21HC AU - Single relay

2961503

<https://www.phoenixcontact.com/us/products/2961503>



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 24 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-120AC/21HC AU - Single relay

2961516

<https://www.phoenixcontact.com/us/products/2961516>




Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 120 V AC

REL-MR-230AC/21HC AU - Single relay

2961529

<https://www.phoenixcontact.com/us/products/2961529>



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 changeover contact, input voltage 230 V AC

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

REL-MR- 12DC/21-21 - Single relay

2961257

<https://www.phoenixcontact.com/us/products/2961257>




Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 12 V DC

REL-MR- 24DC/21-21 - Single relay

2961192

<https://www.phoenixcontact.com/us/products/2961192>



Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 48DC/21-21 - Single relay

2834834

<https://www.phoenixcontact.com/us/products/2834834>




Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 48 V DC

REL-MR- 60DC/21-21 - Single relay

2961273

<https://www.phoenixcontact.com/us/products/2961273>



Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 60 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-110DC/21-21 - Single relay

2961202

<https://www.phoenixcontact.com/us/products/2961202>




Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 110 V DC

REL-MR- 24AC/21-21 - Single relay

2961435

<https://www.phoenixcontact.com/us/products/2961435>



Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 24 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-120AC/21-21 - Single relay

2961448

<https://www.phoenixcontact.com/us/products/2961448>




Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 120 V AC

REL-MR-230AC/21-21 - Single relay

2961451

<https://www.phoenixcontact.com/us/products/2961451>



Plug-in miniature power relay, with power contact, 2 changeover contacts, input voltage 230 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 12DC/21-21AU - Single relay

2961299

<https://www.phoenixcontact.com/us/products/2961299>




Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 12 V DC

REL-MR- 24DC/21-21AU - Single relay

2961215

<https://www.phoenixcontact.com/us/products/2961215>



Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 48DC/21-21AU - Single relay

2834847

<https://www.phoenixcontact.com/us/products/2834847>




Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 48 V DC

REL-MR- 60DC/21-21AU - Single relay

2961286

<https://www.phoenixcontact.com/us/products/2961286>



Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 60 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-110DC/21-21AU - Single relay

2961228

<https://www.phoenixcontact.com/us/products/2961228>




Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 110 V DC

REL-MR- 24AC/21-21AU - Single relay

2961464

<https://www.phoenixcontact.com/us/products/2961464>



Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 24 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-120AC/21-21AU - Single relay

2961477

<https://www.phoenixcontact.com/us/products/2961477>




Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 120 V AC

REL-MR-230AC/21-21AU - Single relay

2961480

<https://www.phoenixcontact.com/us/products/2961480>



Plug-in miniature power relay, with multi-layer gold contact, 2 changeover contacts, input voltage 230 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 24DC/1IC - Single relay

2961341

<https://www.phoenixcontact.com/us/products/2961341>



Pluggable miniature power relay, with power contact for high switch-on currents up to 130 A peaks, 1 N/O contact, input voltage: 24 V DC

REL-MR- 24DC/21HC/MS - Single relay

2987888

<https://www.phoenixcontact.com/us/products/2987888>



Plug-in miniature relay, with power contact, 1 changeover contact, test button, mechanical switching position indicator, status LED, freewheeling diode, polarity A1+, A2-, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 24AC/21HC/MS - Single relay

2987891

<https://www.phoenixcontact.com/us/products/2987891>



Plug-in miniature relay, with power contact, 1 changeover contact, test button, mechanical switching position indicator, status LED, input voltage 24 V AC

REL-MR-120AC/21HC/MS - Single relay

2987901

<https://www.phoenixcontact.com/us/products/2987901>



Plug-in miniature relay, with power contact, 1 changeover contact, test button, mechanical switching position indicator, status LED, input voltage 120 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-230AC/21HC/MS - Single relay

2987914

<https://www.phoenixcontact.com/us/products/2987914>



Plug-in miniature relay, with power contact, 1 changeover contact, test button, mechanical switching position indicator, status LED, input voltage 230 V AC

REL-MR- 24DC/21HC AU/MS - Single relay

2987927

<https://www.phoenixcontact.com/us/products/2987927>



Plug-in miniature relay, with multi-layer contact with hard gold coating, 1 changeover contact, test button, mechanical switching position indicator, status LED, freewheeling diode, polarity A1+, A2-, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-230AC/21HC AU/MS - Single relay

2987930

<https://www.phoenixcontact.com/us/products/2987930>



Plug-in miniature relay, with multi-layer contact with hard gold coating, 1 changeover contact, test button, mechanical switching position indicator, status LED, input voltage 230 V AC

REL-MR- 24DC/21-21/MS - Single relay

2987943

<https://www.phoenixcontact.com/us/products/2987943>



Plug-in miniature relay, with power contact, 2 changeover contacts, test button, mechanical switching position indicator, status LED, freewheeling diode, polarity A1+, A2, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR- 24AC/21-21/MS - Single relay

2987956

<https://www.phoenixcontact.com/us/products/2987956>



Plug-in miniature relay, with power contact, 2 changeover contacts, test button, mechanical switching position indicator, status LED, input voltage 24 V AC

REL-MR-120AC/21-21/MS - Single relay

2987969

<https://www.phoenixcontact.com/us/products/2987969>



Plug-in miniature relay, with power contact, 2 changeover contacts, test button, mechanical switching position indicator, status LED, coil voltage 120 V AC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-230AC/21-21/MS - Single relay

2987972

<https://www.phoenixcontact.com/us/products/2987972>



Plug-in miniature relay, with power contact, 2 changeover contacts, test button, mechanical switching position indicator, status LED, coil voltage 230 V AC

REL-MR- 24DC/21-21AU/MS - Single relay

2987985

<https://www.phoenixcontact.com/us/products/2987985>



Plug-in miniature relay, with multi-layer contact with hard gold coating, 2 changeover contacts, test button, mechanical switching position indicator, status LED, freewheeling diode, polarity A1+, A2-, input voltage 24 V DC

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



REL-MR-230AC/21-21AU/MS - Single relay

2987998

<https://www.phoenixcontact.com/us/products/2987998>



Plug-in miniature relay, with multi-layer contact with hard gold coating, 2 changeover contacts, test button, mechanical switching position indicator, status LED, coil voltage 230 V AC

Accessories

LDP- 12- 24DC - Plug-in module

2833657

<https://www.phoenixcontact.com/us/products/2833657>



Plug-in module, with freewheeling diode and yellow LED, polarity: A1+, A2-, input voltage: 12 ... 24 V DC $\pm 20\%$

PR1-BSP3/2X21 - Relay base



2833534

<https://www.phoenixcontact.com/us/products/2833534>

LDP- 48- 60DC - Plug-in module

2833660

<https://www.phoenixcontact.com/us/products/2833660>



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: **A1+**, **A2-**, input voltage: 48 ... 60 V DC ± 20 %

LDP-110DC - Plug-in module

2833673

<https://www.phoenixcontact.com/us/products/2833673>



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: **A1+**, **A2-**, input voltage: 110 V DC ± 20 %

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



LV- 12- 24UC - Plug-in module

2833712

<https://www.phoenixcontact.com/us/products/2833712>



Plug-in module, for mounting on PR1 and PR2, with varistor and yellow LED, input voltage: 12 ... 24 V AC/ DC ± 20 %

LV-120-230AC/110DC - Plug-in module

2833738

<https://www.phoenixcontact.com/us/products/2833738>



Plug-in module, with varistor and yellow LED, input voltage: 120 ... 230 V AC / 110 V DC ± 20 %

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



V-120-230UC - Plug-in module

2833880

<https://www.phoenixcontact.com/us/products/2833880>



Plug-in module, with varistor, input voltage: 120 ... 230 V AC/DC $\pm 20\%$

RC-120-230UC - Plug-in module

2833767

<https://www.phoenixcontact.com/us/products/2833767>



Plug-in module, with RC element, input voltage: 120 ... 230 V AC/DC $\pm 20\%$

PR1-BSP3/2X21 - Relay base

2833534

<https://www.phoenixcontact.com/us/products/2833534>



MP 1 - Marker labels

2833631

<https://www.phoenixcontact.com/us/products/2833631>

Equipment marker, labeling surface 6 x 15 mm



EML (15X6)R YE - Label

0819288

<https://www.phoenixcontact.com/us/products/0819288>



Label, Roll, yellow, unlabeled, can be labeled with: THERMOMARK E.300 (D)/600 (D), THERMOMARK ROLL 2.0, THERMOMARK ROLL, THERMOMARK ROLL X1, THERMOMARK ROLLMASTER 300/600, THERMOMARK X1.2, mounting type: adhesive, lettering field size: 15 x 6 mm, Number of individual labels: 2500

Phoenix Contact 2024 © - all rights reserved
<https://www.phoenixcontact.com>

Phoenix Contact USA
586 Fulling Mill Road
Middletown, PA 17057, United States
(+717) 944-1300
info@phoenixcon.com