



EV8128-Q-00A

1A, DiSEqC 1.x and 2.x Compatible, LNB Voltage Regulator with I²C Interface Evaluation Board

DESCRIPTION

The EV8128-Q-00A is an evaluation board designed to demonstrate the capabilities of the MP8128, a highly integrated, DiSEqC 1.x and DiSEqC 2.x compatible, low-noise block (LNB) voltage regulator. It provides efficient, low-noise power and interface signals to a satellite receiver's LNB antenna ports.

The device integrates a boost regulator and a tracking linear voltage regulator. The boost regulator provides a power source 1.1V above the LNB output voltage. The tracking linear voltage regulator provides clean power and protects the output from overloads and shorts. The MP8128 features voltage selection, over-current protection (OCP), an I²C interface, and a selectable 22kHz tone signal.

The MP8128 offers a simple solution with a low component count, and is available in a QFN-20 (3mmx3mm) package.

ELECTRICAL SPECIFICATIONS

Parameter	Symbol	Value	Units
Input voltage	V _{IN}	8 to 14	V
LNB output voltage ⁽¹⁾	LNB_OUT	10.33 to 20	V
LNB output current	I _{OUT}	0 to 1	A

Note:

1) Use the I²C interface to set the LNB output voltage.

FEATURES


- 8V to 14V Input Voltage (V_{IN}) Range
- Up to 1A Configurable Current
- DiSEqC 1.x and DiSEqC 2.x Compatible
- Integrated I²C Bus
- Low-Noise LDO Output
- 440kHz Switching Frequency (f_{sw})
- Selectable 22kHz Internal or External Signal Source
- Selectable LNB Output Voltage
- Over-Current Protection (OCP), Short-Circuit Protection (SCP), and Over-Voltage Protection (OVP)
- Thermal Shutdown
- Available in a QFN-20 (3mmx3mm) Package

APPLICATIONS

- LNB Power Supplies and Controls for Satellite Set-Top Boxes
- TV Satellite Receivers
- Personal Computer (PC) Satellite Card Receivers

All MPS parts are lead-free, halogen-free, and adhere to the RoHS directive. For MPS green status, please visit the MPS website under Quality Assurance. "MPS", the MPS logo, and "Simple, Easy Solutions" are trademarks of Monolithic Power Systems, Inc. or its subsidiaries.

EV8128-Q-00A EVALUATION BOARD




LxW (63.5mmx63.5mm)

Board Number	MPS IC Number
EV8128-Q-00A	MP8128GQ

Efficiency vs. Output Current

V_{LNB_OUT} = 18V



QUICK START GUIDE

1. Connect the load ($\leq 1A$) terminals to:
 - a. Positive (+): LNB_OUT
 - b. Negative (-): GND
2. Preset the power supply between 8V and 14V.
3. Turn off the power supply.
4. Connect the power supply terminals to:
 - a. Positive (+): VIN
 - b. Negative (-): GND
5. Install the MP8128 GUI software.⁽²⁾
6. Connect the computer to the board via the USB cable.⁽³⁾
7. Turn on the power supply.
8. Open the GUI, then click the “Part Numbers” drop-down menu. Select “MP8128” in the drop-down menu.
9. Set the MP8128 registers via the I²C. ⁽⁴⁾ To set the registers, follow steps 10 through 12:
10. Read UVLO status register 02h, bit[3].
11. To set the LNB voltage (V_{LNB_OUT}), write VSEL register 00h, bits[4:3]. For example, to set V_{LNB_OUT} to 18V, write 11 to bits[4:3].
12. To set the LNB line drop voltage compensation, write the VLINE register 00h, bits[2:0]. To set the voltage compensation to 0V, write 000 to bits[2:0]. Once VLINE is changed from 111 to any other value, the board should start up automatically.

Notes:

- 2) The MPS GUI software can be downloaded from the MPS website.
- 3) The EVKT-MP8128 includes a USB to I²C communication interface for GUI control.
- 4) The MP8128 address is set to 0x08h by default.

EVALUATION BOARD SCHEMATIC




Figure 1: Evaluation Board Schematic (5)

Note:







5) The MP8128 address is set to 0x08h by default.

EV8128-Q-00A BILL OF MATERIALS

Qty	Ref	Value	Description	Package	Manufacturer	Manufacturer PN
3	C1A, C3B, C3C	10 μ F	Ceramic capacitor, 25V, X7R	1210	Murata	GRM32DR71E106KA12L
4	C1B, C2, C3A, C4	0.1 μ F	Ceramic capacitor, 50V, X7R	0603	Murata	GRM188R71H104KA93D
1	C5	10nF	Ceramic capacitor, 16V, X7R	0603	Murata	GRM188R71H103KA01D
1	C6	4.7nF	Ceramic capacitor, 50V, X7R	0603	Murata	GRM188R71H472KA01D
1	C7	0.22 μ F	Ceramic capacitor, 25V, X7R	0603	Murata	GRM188R71E224KA88D
1	C8	22nF	Ceramic capacitor, 25V, X7R	0603	Murata	GRM188R71E223KA01D
1	R1	6.98k Ω	Film resolution, 1%	0603	Yageo	RC0603FR-076K98L
2	R2, R11	100k Ω	Film resolution, 1%	0603	Royal Ohm	RL0603FR-07100KL
0	R3	NS				
1	R4	100 Ω	Film resolution, 1%	0603	Royal Ohm	RL0603FR-07100RL
1	R5	6.8k Ω	Film resolution, 1%	0603	Royal Ohm	RL0603FR-076K8L
8	R6, R7, R8, R9, R12, R13, R14, R15	10k Ω	Film resolution, 1%	0603	Royal Ohm	RL0603FR-0710KL
1	R10	15 Ω	Film resolution, 1%	0805	Yageo	RC0805FR-0715RL
1	R16	0 Ω	Film resolution, 1%	0603	Yageo	RC0603FR-070RL
1	L1	10 μ H	Inductor, DCR = 16.3m Ω , I _{RATED} = 7.2A, I _{SAT} = 8.5A	SMD	Würth	7443251000
1	L2	220 μ H	Inductor, DCR = 434m Ω , I _{SAT} = 1.47A	SMD	TDK	VLF10045T-221MR90
1	D1	40V	Schottky diode, 3A	SMA	Diodes, Inc.	B340
1	D2	40V	Schottky diode, 1A	SOD-123	Diodes, Inc.	1N5819HW
1	Q1	25V	NPN, BJT transistor, 625mW, 1.5A	SOT-23	Any	
1	Q2	340m Ω	P-channel MOSFET, 60V, 1.25A	SOT-23	Vishay	SI2309DS-T1-E3
1	U1	MP8128	LNB power regulator with I ² C interface, 1A	QFN-20 (3mmx3mm)	MPS	MP8128GQ







EVB TEST RESULTS

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.



EVB TEST RESULTS (continued)


Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.




EV8 TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Steady State

 $I_{OUT} = 0A$



Steady State

 $I_{OUT} = 0.6A$



Start-Up through the I²C

 $I_{OUT} = 0A$, VLINE bits set to 000



Start-Up through the I²C

 $I_{OUT} = 1A$, VLINE bits set to 000


Shutdown through the I²C

 $I_{OUT} = 0A$, VLINE bits set to 111



Shutdown through the I²C

 $I_{OUT} = 1A$, VLINE bits set to 111



EVB TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Shutdown through VIN

 $I_{OUT} = 0A$



Shutdown through VIN

 $I_{OUT} = 1A$



Shutdown through EN

 $I_{OUT} = 0A$



Shutdown through EN

 $I_{OUT} = 1A$


SCP Entry

 $I_{OUT} = 0A$, $OCR = 0$, $DCL = 1$


SCP Recovery


 $I_{OUT} = 0A$, $OCR = 0$, $DCL = 1$


EVB TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


SCP Entry

$I_{OUT} = 1A$, $OCR = 0$, $DCL = 1$




SCP Recovery

$I_{OUT} = 1A$, $OCR = 0$, $DCL = 1$




Load Transient

$I_{OUT} = 0A$ to $0.3A$




Load Transient

$I_{OUT} = 0.3A$ to $0.6A$




Switching from 13V to 18V

$I_{OUT} = 0A$



Switching from 13V to 18V


$I_{OUT} = 0.6A$




EVB TEST RESULTS (continued)

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Switching from 18V to 13V

 $I_{OUT} = 0A$



Switching from 18V to 13V

 $I_{OUT} = 0.6A$



Tone Signal Steady State

 $EXTM = 2V$, $TCTRL = 0$, $I_{OUT} = 0A$



Tone Signal Steady State

 $EXTM = 2V$, $TCTRL = 0$, $I_{OUT} = 1A$


Tone Signal Steady State

 $EXTM = 22kHz$ square wave, $TCTRL = 1$, $I_{OUT} = 0A$


Tone Signal Steady State


 $EXTM = 22kHz$ square wave, $TCTRL = 1$, $I_{OUT} = 1A$


EVB TEST RESULTS *(continued)*

Performance waveforms are tested on the evaluation board. $V_{IN} = 12V$, $V_{LNB_OUT} = 18V$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Tone Entry

EXTM = 3.3V, TCTRL = 0, $I_{OUT} = 0A$,
TEN = 0 to 1




Tone Exit

EXTM = 3.3V, TCTRL = 0, $I_{OUT} = 0A$,
TEN = 1 to 0



Tone Signal Detected from Load

DiSEqC 2.0 output load = 0mA to 40mA,
load transient frequency = 22kHz,
50% duty cycle



PCB LAYOUT




Figure 2: Top Silk




Figure 3: Top Layer




Figure 4: Bottom Layer




Figure 5: Bottom Silk



REVISION HISTORY

Revision #	Revision Date	Description	Pages Updated
1.0	12/18/2017	Initial Release	-
1.1	9/23/2021	Grammar and formatting updates, including headers and footers	All

Notice: The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.