

Part Number: 08700069

Product Description: KK Cat Ear Crimp Terminal 5159, 22-28 AWG, Bag, Brass, Tin (Sn) over Copper Plating

**Status:** New Business Not Supported

**Engineering Number: 5159TL** 

Series Number: 5159

**Product Category:** Crimp Terminals

Packaging Alternative: 08700064 (Reel)

### **Documents & Resources**

**Tooling Specifications** 

Crimp Specification CS-5159-001.pdf

## **Product Environment Compliance**

### Compliance

GADSL/IMDS	Compliant with Exemption 44
China RoHS	<b>©</b>
EU ELV	Not Relevant
Low-Halogen Status	Low-Halogen per IEC 61249-2-21
REACH SVHC	Not Contained per D(2024)4144-DC (27 June 2024)
EU RoHS	Compliant per EU 2015/863

### **Multiple Part Product Compliance Statements**

- Eu RoHS
- REACH SVHC
- Low-Halogen

### Multiple Part Industry Compliance Documents

- IPC 1752A Class C
- IPC 1752A Class D
- Molex Product Compliance Declaration
- IEC-62474
- chemSHERPA (xml)

## **EU RoHS Certificate of Compliance**

#### **Part Details**

#### General

Status	New Business Not Supported
Category	Crimp Terminals
Series	5159
Description	KK Cat Ear Crimp Terminal 5159, 22-28 AWG, Bag, Brass, Tin (Sn) over Copper Plating
Application	Signal, Wire-to-Board
Product Family	KK Interconnect Systems
Product Name	Cat Ear,KK
UPC	800753534834

# Physical

Gender	Female
Material - Metal	Brass
Material - Plating Mating	Tin
Material - Plating Termination	Tin
Net Weight	40.000/mg
Packaging Type	Bag
Plating min - Mating	0.889µm
Plating min - Termination	0.889µm
Termination Interface Style	Crimp or Compression
Wire Insulation Diameter	1.20-1.70mm
Wire Size (AWG)	22, 24, 26, 28
Wire Size mm²	N/A

# **Application Tooling**

## Global

Description	Part Number
Extraction Tool for KK 2.54mm Terminals, 22-30 AWG	11030022
PremiumGrade Hand Crimp Tool for KK 2.54mm Crimp Terminals, 22-30 AWG	<u>638118200</u>
Insertion Tool for KK 2.54mm Terminals, 22-30 AWG	638120000

# **Application Tooling**

## Japan

Description	Part Number
Hand Extraction Tool	11260059

This document was generated on Aug 13, 2024